

## Overview of Charging Characteristics 2BJ415AC1

No.	Battery voltage	Battery type	Battery capacity	I <sub>1</sub>	U <sub>1</sub>	I <sub>2</sub>	I <sub>3</sub>	U <sub>3</sub>	TI <sub>1 max</sub>	TU <sub>1 max</sub>	TU <sub>3</sub>	Note
0	12 V	FVLA	150 Ah ... 200 Ah	50 A	14,4 V	3,6 A	13,5 V	50 A	5 h	6 h	∞	
1	12 V	FVLA	200 Ah ... 280 Ah	60 A	14,4 V	4,8 A	13,5 V	60 A	6 h	7 h	∞	
2	12 V	FVLA	280 Ah ... 380 Ah	60 A	14,4 V	6,6 A	13,5 V	60 A	8 h	9 h	∞	
3	12 V	FVLA	380 Ah ... 500 Ah	60 A	14,4 V	8,8 A	13,5 V	60 A	11 h	2 h	∞	
4	12 V	FVLA	500 Ah ... 600 Ah	60 A	14,4 V	11 A	13,5 V	60 A	11 h	12 h	∞	
5	12 V	VRLA	150 Ah ... 200 Ah	50 A	14,1 V	1,8 A	13,6 V	50 A	5 h	6 h	∞	
6	12 V	VRLA	200 Ah ... 280 Ah	60 A	14,1 V	2,4 A	13,6 V	60 A	6 h	7 h	∞	
7	12 V	VRLA	280 Ah ... 380 Ah	60 A	14,1 V	3,4 A	13,6 V	60 A	8 h	9 h	∞	
8	12 V	VRLA	380 Ah ... 500 Ah	60 A	14,1 V	4,4 A	13,6 V	60 A	11 h	2 h	∞	
9	12 V	VRLA	500 Ah ... 600 Ah	60 A	14,1 V	5,6 A	13,6 V	60 A	11 h	12 h	∞	
A	12 V	VRLA*	150 Ah ... 200 Ah	50 A	14,4 V	1,8 A	13,8 V	50 A	7 h	8 h	∞	
B	12 V	VRLA*	200 Ah ... 280 Ah	60 A	14,4 V	2,4 A	13,8 V	60 A	7,5 h	8,5 h	∞	
C	12 V	VRLA*	280 Ah ... 380 Ah	60 A	14,4 V	3,4 A	13,8 V	60 A	8 h	9 h	∞	
D	12 V	VRLA*	380 Ah ... 500 Ah	60 A	14,4 V	4,4 A	13,8 V	60 A	10 h	11 h	∞	
E	12 V	VRLA*	500 Ah ... 600 Ah	60 A	14,4 V	5,6 A	13,8 V	60 A	13 h	14 h	∞	
F	13,8 V	Power Supply	n/a	60 A	13,8 V	n/a	13,8 V	60 A	∞	∞	∞	

**FVLA:** open lead-acid batteries, batteries with water refill

**VRLA:** Valve-regulated lead-acid batteries, maintenance-free wet batteries

**VRLA\*:** Gel batteries, AGM

### Description

1. If a temperature sensor (CTS/TS) is connected and the battery temperature is higher than 45°C, the charging current is reduced to 50%. Only when the battery temperature falls below 40°C again does the charging capacity increase to 100%.
2. If a temperature sensor (CTS/TS) is connected and the battery temperature is higher than 50°C, the charger switches off until the battery temperature is below 45°C.
3. If a temperature sensor (CTS/TS) is connected, the output voltage will be increased by 42 mV per degree if the battery temperature is below 25°C and decreased if the battery temperature is above 25°C.
4. If the time TI<sub>1 max</sub> is exceeded, the charger switches off and the red LED flashes.
5. If the time TU<sub>1 max</sub> is exceeded, the next charging phase begins automatically.

