

Übersicht Ladekennlinien BA015A3

Overview charging characteristic BA015A3

Nr. No.	Funktion Function	Ausgangsspannung Output current	I	U _{max}
0	PC-Controlled PAC	0,0 V	0 A	0 V
1	Power Supply	6,1 V	60 A	36 V
2	Power Supply	8,0 V	60 A	36 V
3	Power Supply	10,0 V	60 A	36 V
4	Power Supply	12,0 V	60 A	36 V
5	Power Supply	13,8 V	60 A	36 V
6	Power Supply	16,0 V	60 A	36 V
7	Power Supply	18,1 V	60 A	36 V
8	Power Supply	20,0 V	60 A	36 V
9	Power Supply	24,0 V	60 A	36 V
A	Power Supply	25,0 V	60 A	36 V
B	Power Supply	26,0 V	60 A	36 V
C	Power Supply	27,3 V	60 A	36 V
D	Power Supply	28,0 V	60 A	36 V
E	Power Supply	28,8 V	60 A	36 V
F	Power Supply	36,0 V	60 A	36 V